2.5V Single Data Rate 1:10 Clock Buffer Terabuffer™

5T907

PRODUCT DISCONTINUATION NOTICE - LAST TIME BUY EXPIRES SEPTEMBER 7, 2016 **DATASHEET**

FEATURES:

- Guaranteed Low Skew < 125ps (max)
- Very low duty cycle distortion
- High speed propagation delay < 2.5ns. (max)
- Up to 250MHz operation
- Very low CMOS power levels
- 1.5V V_{DDQ} for HSTL interface
- Hot insertable and over-voltage tolerant inputs
- 3-level inputs for selectable interface
- Selectable HSTL, eHSTL, 1.8V / 2.5V LVTTL, or LVEPECL input interface
- Selectable differential or single-ended inputs and ten single-ended outputs
- 2.5V V_{DD}
- Available in TSSOP package
- *NOT RECOMMENDED FOR NEW DESIGNS*
- *For new designs use functional replacement 8T39S11*

APPLICATIONS:


- Clock and signal distribution

DESCRIPTION:

The 5T907 2.5V single data rate (SDR) clock buffer is a user-selectable single-ended or differential input to ten single-ended outputs buffer built on advanced metal CMOS technology. The SDR clock buffer fanout from a single or differential input to ten single-ended outputs reduces the loading on the preceding driver and provides an efficient clock distribution network. The 5T907 can act as a translator from a differential HSTL, eHSTL, 1.8V/2.5V LVTTL, LVEPECL, or single-ended 1.8V/2.5V LVTTL input to HSTL, eHSTL, 1.8V/2.5V LVTTL outputs. Selectable interface is controlled by 3-level input signals that may be hard-wired to appropriate high-mid-low levels.


The 5T907 has two output banks that can be asynchronously enabled/disabled. Multiple power and grounds reduce noise.

FUNCTIONAL BLOCK DIAGRAM



© 2019 Renesas Electronics Corporation

PIN CONFIGURATION



TSSOP
TOP VIEW

ABSOLUTE MAXIMUM RATINGS(1)

Symbol	Description	Max	Unit
V_{DD}	Power Supply Voltage(2)	–0.5 to +3.6	V
V_{DDQ}	Output Power Supply(2)	–0.5 to +3.6	V
V_I	Input Voltage	–0.5 to +3.6	V
V_O	Output Voltage(3)	–0.5 to V_{DDQ} +0.5	V
V_{REF}	Reference Voltage(3)	–0.5 to +3.6	V
T_{STG}	Storage Temperature	–65 to +165	°C
T_J	Junction Temperature	150	°C

NOTES:
1. Stresses greater than those listed under ABSOLUTE MAXIMUM RATINGS may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect reliability.
2. V_{DDQ} and V_{DD} internally operate independently. No power sequencing requirements need to be met.
3. Not to exceed 3.6V.

CAPACITANCE(1) (T_A = +25°C, F = 1.0MHz)

Symbol	Parameter	Min	Typ.	Max.	Unit
C_{IN}	Input Capacitance	—	3.5	—	pF

NOTE:
1. This parameter is measured at characterization but not tested. Capacitance applies to all inputs except RxS and TxS.

RECOMMENDED OPERATING RANGE

Symbol	Description	Min.	Typ.	Max.	Unit
T_A	Ambient Operating Temperature	–40	+25	+85	°C
V_{DD}(1)	Internal Power Supply Voltage	2.4	2.5	2.6	V
V_{DDQ}(1)	HSTL Output Power Supply Voltage	1.4	1.5	1.6	V
	Extended HSTL and 1.8V LVTTL Output Power Supply Voltage	1.65	1.8	1.95	V
	2.5V LVTTL Output Power Supply Voltage		V_{DD}		V
V_T	Termination Voltage		V_{DDQ} / 2		V

NOTE:
1. All power supplies should operate in tandem; if V_{DD} or V_{DDQ} is at a maximum, then V_{DDQ} or V_{DD} (respectively) should be at a maximum, and vice-versa.

© 2019 Renesas Electronics Corporation

PIN DESCRIPTION

Symbol	I/O	Type	Description
A	I	Adjustable(1)	Clock input. A is the "true" side of the differential clock input. If operating in single-ended mode, A is the clock input.
$\overline{A}/V_{REF}$	I	Adjustable(1)	Complementary clock input. $\overline{A}/V_{REF}$ is the "complementary" side of A if the input is in differential mode. If operating in single-ended mode, $\overline{A}/V_{REF}$ is connected to GND. For single-ended operation in differential mode, $\overline{A}/V_{REF}$ should be set to the desired toggle voltage for A: 2.5V LVTTL V_{REF} = 1250mV 1.8V LVTTL, eHSTL V_{REF} = 900mV HSTL V_{REF} = 750mV LVEPECL V_{REF} = 1082mV
$\overline{G1}$	I	LVTTL(5)	Gate for outputs Q_1 through Q_5. When $\overline{G1}$ is LOW, these outputs are enabled. When $\overline{G1}$ is HIGH, these outputs are asynchronously disabled to the level designated by GL(4).
$\overline{G2}$	I	LVTTL(5)	Gate for outputs Q_6 through Q_{10}. When $\overline{G2}$ is LOW, these outputs are enabled. When $\overline{G2}$ is HIGH, these outputs are asynchronously disabled to the level designated by GL(4).
GL	I	LVTTL(5)	Specifies output disable level. If HIGH, the outputs disable HIGH. If LOW, the outputs disable LOW.
Qn	O	Adjustable(2)	Clock outputs
RxS	I	3 Level(3)	Selects single-ended 2.5V LVTTL (HIGH), 1.8V LVTTL (MID) clock input or differential (LOW) clock input
TxS	I	3 Level(3)	Sets the drive strength of the output drivers to be 2.5V LVTTL (HIGH), 1.8V LVTTL (MID) or HSTL (LOW) compatible. Used in conjunction with V_{DDO} to set the interface levels.
V_{DD}		PWR	Power supply for the device core and inputs
V_{DDO}		PWR	Power supply for the device outputs. When utilizing 2.5V LVTTL outputs, V_{DDO} should be connected to V_{DD}.
GND		PWR	Power supply return for all power

NOTES:

1. Inputs are capable of translating the following interface standards. User can select between:
   Single-ended 2.5V LVTTL levels
   Single-ended 1.8V LVTTL levels
   or
   Differential 2.5V/1.8V LVTTL levels
   Differential HSTL and eHSTL levels
   Differential LVEPECL levels
2. Outputs are user selectable to drive 2.5V, 1.8V LVTTL, eHSTL, or HSTL interface levels when used with the appropriate V_{DDQ} voltage.
3. 3 level inputs are static inputs and must be tied to V_{DD} or GND or left floating. These inputs are not hot-insertable or over-voltage tolerant.
4. Because the gate controls are asynchronous, runt pulses are possible. It is the user's responsibility to either time the gate control signals to minimize the possibility of runt pulses or be able to tolerate them in down stream circuitry.
5. Pins listed as LVTTL inputs will accept 2.5V signals when RxS = HIGH or 1.8V signals when RxS = LOW or MID.

© 2019 Renesas Electronics Corporation

INPUT/OUTPUT SELECTION(1)

Input	Output
2.5V LVTTL SE	2.5V LVTTL
1.8V LVTTL SE	
2.5V LVTTL DSE	
1.8V LVTTL DSE	
LVEPECL DSE	
eHSTL DSE	
HSTL DSE	
2.5V LVTTL DIF	
1.8V LVTTL DIF	
LVEPECL DIF	
eHSTL DIF	
HSTL DIF	
2.5V LVTTL SE	1.8V LVTTL
1.8V LVTTL SE	
2.5V LVTTL DSE	
1.8V LVTTL DSE	
LVEPECL DSE	
eHSTL DSE	
HSTL DSE	
2.5V LVTTL DIF	
1.8V LVTTL DIF	
LVEPECL DIF	
eHSTL DIF	
HSTL DIF	

Input	Output
2.5V LVTTL SE	eHSTL
1.8V LVTTL SE	
2.5V LVTTL DSE	
1.8V LVTTL DSE	
LVEPECL DSE	
eHSTL DSE	
HSTL DSE	
2.5V LVTTL DIF	
1.8V LVTTL DIF	
LVEPECL DIF	
eHSTL DIF	
HSTL DIF	
2.5V LVTTL SE	HSTL
1.8V LVTTL SE	
2.5V LVTTL DSE	
1.8V LVTTL DSE	
LVEPECL DSE	
eHSTL DSE	
HSTL DSE	
2.5V LVTTL DIF	
1.8V LVTTL DIF	
LVEPECL DIF	
eHSTL DIF	
HSTL DIF	

NOTE:
1. The INPUT/OUTPUT SELECTION Table describes the total possible combinations of input and output interfaces. Single-Ended (SE) inputs in a single-ended mode require the $\overline{A}/V_{REF}$ pin to be connected to GND. Differential Single-Ended (DSE) is for single-ended operation in differential mode, requiring a V_{REF}. Differential (DIF) inputs are used only in differential mode.

DC ELECTRICAL CHARACTERISTICS OVER OPERATING RANGE

Symbol	Parameter	Test Conditions		Min.	Max	Unit
V_{IHH}	Input HIGH Voltage Level(1)	3-Level Inputs Only		V_{DD} – 0.4	—	V
V_{IMM}	Input MID Voltage Level(1)	3-Level Inputs Only		$V_{DD}/2$ – 0.2	$V_{DD}/2$ + 0.2	V
V_{ILL}	Input LOW Voltage Level(1)	3-Level Inputs Only		—	0.4	V
I_3	3-Level Input DC Current (RxS, TxS)	$V_{IN} = V_{DD}$	HIGH Level	—	200	µA
		$V_{IN} = V_{DD}/2$	MID Level	–50	+50	
		V_{IN} = GND	LOW Level	–200	—	

NOTE:
1. These inputs are normally wired to V_{DD}, GND, or left floating. Internal temination resistors bias unconnected inputs to $V_{DD}/2$.

© 2019 Renesas Electronics Corporation

DC ELECTRICAL CHARACTERISTICS OVER OPERATING RANGE FOR HSTL(1)

Symbol	Parameter	Test Conditions	Min.	Typ.(7)	Max	Unit
Input Characteristics						
I_{IH}	Input HIGH Current(9)	V_{DD} = 2.6V V_I = V_{DDQ}/GND	—	—	±5	µA
I_{IL}	Input LOW Current(9)	V_{DD} = 2.6V V_I = GND/V_{DDQ}	—	—	±5	
V_{IK}	Clamp Diode Voltage	V_{DD} = 2.4V, I_{IN} = -18mA	—	- 0.7	- 1.2	V
V_{IN}	DC Input Voltage		- 0.3		+3.6	V
V_{DIF}	DC Differential Voltage(2,8)		0.2		—	V
V_{CM}	DC Common Mode Input Voltage(3,8)		680	750	900	mV
V_{IH}	DC Input HIGH(4,5,8)		V_{REF} + 100		—	mV
V_{IL}	DC Input LOW(4,6,8)		—		V_{REF} - 100	mV
V_{REF}	Single-Ended Reference Voltage(4,8)		—	750	—	mV
Output Characteristics						
V_{OH}	Output HIGH Voltage	I_{OH} = -8mA	V_{DDQ} - 0.4		—	V
		I_{OH} = -100µA	V_{DDQ} - 0.1		—	V
V_{OL}	Output LOW Voltage	I_{OL} = 8mA	—		0.4	V
		I_{OL} = 100µA	—		0.1	V

NOTES:

1. See RECOMMENDED OPERATING RANGE table.
2. V_{DIF} specifies the minimum input differential voltage (V_{TR} - V_{CP}) required for switching where V_{TR} is the "true" input level and V_{CP} is the "complement" input level. Differential mode only. The DC differential voltage must be maintained to guarantee retaining the existing HIGH or LOW input. The AC differential voltage must be achieved to guarantee switching to a new state.
3. V_{CM} specifies the maximum allowable range of (V_{TR} + V_{CP}) /2. Differential mode only.
4. For single-ended operation, in differential mode, $\overline{A}/V_{REF}$ is tied to the DC voltage V_{REF}.
5. Voltage required to maintain a logic HIGH, single-ended operation in differential mode.
6. Voltage required to maintain a logic LOW, single-ended operation in differential mode.
7. Typical values are at V_{DD} = 2.5V, V_{DDQ} = 1.5V, +25°C ambient.
8. The reference clock input is capable of HSTL, eHSTL, LVEPECL, 1.8V or 2.5V LVTTL operation independent of the device output. The correct input interface table should be referenced.
9. For differential mode (RxS = LOW), A and $\overline{A}/V_{REF}$ must be at the opposite rail.

POWER SUPPLY CHARACTERISTICS FOR HSTL OUTPUTS(1)

Symbol	Parameter	Test Conditions(2)	Typ.	Max	Unit
I_{DDQ}	Quiescent V_{DD} Power Supply Current	V_{DDQ} = Max., Reference Clock = LOW(3) Outputs enabled, All outputs unloaded	20	30	mA
I_{DDQQ}	Quiescent V_{DDQ} Power Supply Current	V_{DDQ} = Max., Reference Clock = LOW(3) Outputs enabled, All outputs unloaded	0.1	0.3	mA
I_{DDD}	Dynamic V_{DD} Power Supply Current per Output	V_{DD} = Max., V_{DDQ} = Max., C_L = 0pF	20	30	µA/MHz
I_{DDDQ}	Dynamic V_{DDQ} Power Supply Current per Output	V_{DD} = Max., V_{DDQ} = Max., C_L = 0pF	30	50	µA/MHz
I_{TOT}	Total Power V_{DD} Supply Current	V_{DDQ} = 1.5V, $F_{REFERENCE\ CLOCK}$ = 100MHz, C_L = 15pF	20	40	mA
		V_{DDQ} = 1.5V, $F_{REFERENCE\ CLOCK}$ = 250MHz, C_L = 15pF	35	50	
I_{TOTQ}	Total Power V_{DDQ} Supply Current	V_{DDQ} = 1.5V, $F_{REFERENCE\ CLOCK}$ = 100MHz, C_L = 15pF	35	70	mA
		V_{DDQ} = 1.5V, $F_{REFERENCE\ CLOCK}$ = 250MHz, C_L = 15pF	50	100	

NOTES:

1. These power consumption characteristics are for all the valid input interfaces and cover the worst case input and output interface combinations.
2. The termination resistors are excluded from these measurements.
3. If the differential input interface is used, the true input is held LOW and the complementary input is held HIGH.

© 2019 Renesas Electronics Corporation

DIFFERENTIAL INPUT AC TEST CONDITIONS FOR HSTL

Symbol	Parameter	Value	Units
V_{DIF}	Input Signal Swing(1)	1	V
V_X	Differential Input Signal Crossing Point(2)	750	mV
V_{THI}	Input Timing Measurement Reference Level(3)	Crossing Point	V
t_R, t_F	Input Signal Edge Rate(4)	1	V/ns

NOTES:

1. The 1V peak-to-peak input pulse level is specified to allow consistent, repeatable results in an automatic test equipment (ATE) environment. Compliant devices must meet the V_{DIF} (AC) specification under actual use conditions.
2. A 750mV crossing point level is specified to allow consistent, repeatable results in an automatic test equipment (ATE) environment. Compliant devices must meet the V_X specification under actual use conditions.
3. In all cases, input waveform timing is marked at the differential cross-point of the input signals.
4. The input signal edge rate of 1V/ns or greater is to be maintained in the 20% to 80% range of the input waveform.

DC ELECTRICAL CHARACTERISTICS OVER OPERATING RANGE FOR eHSTL(1)

Symbol	Parameter	Test Conditions	Min.	Typ.(7)	Max	Unit
Input Characteristics						
I_{IH}	Input HIGH Current(9)	V_{DD} = 2.6V V_I = V_{DDQ}/GND	—	—	±5	µA
I_{IL}	Input LOW Current(9)	V_{DD} = 2.6V V_I = GND/V_{DDQ}	—	—	±5	
V_{IK}	Clamp Diode Voltage	V_{DD} = 2.4V, I_{IN} = -18mA	—	- 0.7	- 1.2	V
V_{IN}	DC Input Voltage		- 0.3		+3.6	V
V_{DIF}	DC Differential Voltage(2,8)		0.2		—	V
V_{CM}	DC Common Mode Input Voltage(3,8)		800	900	1000	mV
V_{IH}	DC Input HIGH(4,5,8)		V_{REF} + 100		—	mV
V_{IL}	DC Input LOW(4,6,8)		—		V_{REF} - 100	mV
V_{REF}	Single-Ended Reference Voltage(4,8)		—	900	—	mV
Output Characteristics						
V_{OH}	Output HIGH Voltage	I_{OH} = -8mA	V_{DDQ} - 0.4		—	V
		I_{OH} = -100µA	V_{DDQ} - 0.1		—	V
V_{OL}	Output LOW Voltage	I_{OL} = 8mA	—		0.4	V
		I_{OL} = 100µA	—		0.1	V

NOTES:

1. See RECOMMENDED OPERATING RANGE table.
2. V_{DIF} specifies the minimum input differential voltage (V_{TR} - V_{CP}) required for switching where V_{TR} is the "true" input level and V_{CP} is the "complement" input level. Differential mode only. The DC differential voltage must be maintained to guarantee retaining the existing HIGH or LOW input. The AC differential voltage must be achieved to guarantee switching to a new state.
3. V_{CM} specifies the maximum allowable range of (V_{TR} + V_{CP}) /2. Differential mode only.
4. For single-ended operation, in a differential mode, $\overline{A}$/V_{REF} is tied to the DC voltage V_{REF}.
5. Voltage required to maintain a logic HIGH, single-ended operation in differential mode.
6. Voltage required to maintain a logic LOW, single-ended operation in differential mode.
7. Typical values are at V_{DD} = 2.5V, V_{DDQ} = 1.8V, +25°C ambient.
8. The reference clock input is capable of HSTL, eHSTL, LVEPECL, 1.8V or 2.5V LVTTL operation independent of the device output. The correct input interface table should be referenced.
9. For differential mode (RxS = LOW), A and $\overline{A}$/V_{REF} must be at the opposite rail.

© 2019 Renesas Electronics Corporation

POWER SUPPLY CHARACTERISTICS FOR eHSTL OUTPUTS(1)

Symbol	Parameter	Test Conditions(2)	Typ.	Max	Unit
I_{DDQ}	Quiescent V_{DD} Power Supply Current	V_{DDQ} = Max., Reference Clock = LOW(3) Outputs enabled, All outputs unloaded	20	30	mA
I_{DDQQ}	Quiescent V_{DDQ} Power Supply Current	V_{DDQ} = Max., Reference Clock = LOW(3) Outputs enabled, All outputs unloaded	0.1	0.3	mA
I_{DDD}	Dynamic V_{DD} Power Supply Current per Output	V_{DD} = Max., V_{DDQ} = Max., C_L = 0pF	20	30	µA/MHz
I_{DDDQ}	Dynamic V_{DDQ} Power Supply Current per Output	V_{DD} = Max., V_{DDQ} = Max., C_L = 0pF	40	60	µA/MHz
I_{TOT}	Total Power V_{DD} Supply Current	V_{DDQ} = 1.8V, $F_{REFERENCE\ CLOCK}$ = 100MHz, C_L = 15pF	20	40	mA
		V_{DDQ} = 1.8V, $F_{REFERENCE\ CLOCK}$ = 250MHz, C_L = 15pF	35	50	
I_{TOTQ}	Total Power V_{DDQ} Supply Current	V_{DDQ} = 1.8V, $F_{REFERENCE\ CLOCK}$ = 100MHz, C_L = 15pF	40	80	mA
		V_{DDQ} = 1.8V, $F_{REFERENCE\ CLOCK}$ = 250MHz, C_L = 15pF	80	160	

NOTES:

1. These power consumption characteristics are for all the valid input interfaces and cover the worst case input and output interface combinations.
2. The termination resistors are excluded from these measurements.
3. If the differential input interface is used, the true input is held LOW and the complementary input is held HIGH.

DIFFERENTIAL INPUT AC TEST CONDITIONS FOR eHSTL

Symbol	Parameter	Value	Units
V_{DIF}	Input Signal Swing(1)	1	V
V_X	Differential Input Signal Crossing Point(2)	900	mV
V_{THI}	Input Timing Measurement Reference Level(3)	Crossing Point	V
t_R, t_F	Input Signal Edge Rate(4)	1	V/ns

NOTES:

1. The 1V peak-to-peak input pulse level is specified to allow consistent, repeatable results in an automatic test equipment (ATE) environment. Compliant devices must meet the V_{DIF} (AC) specification under actual use conditions.
2. A 900mV crossing point level is specified to allow consistent, repeatable results in an automatic test equipment (ATE) environment. Compliant devices must meet the V_X specification under actual use conditions.
3. In all cases, input waveform timing is marked at the differential cross-point of the input signals.
4. The input signal edge rate of 1V/ns or greater is to be maintained in the 20% to 80% range of the input waveform.

DC ELECTRICAL CHARACTERISTICS OVER OPERATING RANGE FOR LVEPECL(1)

Symbol	Parameter	Test Conditions	Min.	Typ.(2)	Max	Unit
Input Characteristics						
I_{IH}	Input HIGH Current(6)	V_{DD} = 2.6V V_I = V_{DDQ}/GND	—	—	±5	µA
I_{IL}	Input LOW Current(6)	V_{DD} = 2.6V V_I = GND/V_{DDQ}	—	—	±5	
V_{IK}	Clamp Diode Voltage	V_{DD} = 2.4V, I_{IN} = -18mA	—	- 0.7	- 1.2	V
V_{IN}	DC Input Voltage		- 0.3	—	3.6	V
V_{CM}	DC Common Mode Input Voltage(3,5)		915	1082	1248	mV
V_{REF}	Single-Ended Reference Voltage(4,5)		—	1082	—	mV
V_{IH}	DC Input HIGH		1275	—	1620	mV
V_{IL}	DC Input LOW		555	—	875	mV

NOTES:

1. See RECOMMENDED OPERATING RANGE table.
2. Typical values are at V_{DD} = 2.5V, +25°C ambient.
3. V_{CM} specifies the maximum allowable range of (V_{TR} + V_{CP}) /2. Differential mode only.
4. For single-ended operation while in differential mode, $\overline{A}/V_{REF}$ is tied to the DC voltage V_{REF}.
5. The reference clock input is capable of HSTL, eHSTL, LVEPECL, 1.8V or 2.5V LVTTL operation independent of the device output. The correct input interface table should be referenced.
6. For differential mode (RxS = LOW), A and $\overline{A}/V_{REF}$ must be at the opposite rail.

© 2019 Renesas Electronics Corporation

DIFFERENTIAL INPUT AC TEST CONDITIONS FOR LVEPECL

Symbol	Parameter	Value	Units
V_{DIF}	Input Signal Swing(1)	732	mV
V_X	Differential Input Signal Crossing Point(2)	1082	mV
V_{THI}	Input Timing Measurement Reference Level(3)	Crossing Point	V
t_R, t_F	Input Signal Edge Rate(4)	1	V/ns

NOTES:

1. The 732mV peak-to-peak input pulse level is specified to allow consistent, repeatable results in an automatic test equipment (ATE) environment. Compliant devices must meet the V_{DIF} (AC) specification under actual use conditions.
2. A 1082mV crossing point level is specified to allow consistent, repeatable results in an automatic test equipment (ATE) environment. Compliant devices must meet the V_X specification under actual use conditions.
3. In all cases, input waveform timing is marked at the differential cross-point of the input signals.
4. The input signal edge rate of 1V/ns or greater is to be maintained in the 20% to 80% range of the input waveform.

DC ELECTRICAL CHARACTERISTICS OVER OPERATING RANGE FOR 2.5V LVTTL(1)

Symbol	Parameter	Test Conditions	Min.	Typ.(8)	Max	Unit
Input Characteristics						
I_{IH}	Input HIGH Current(10)	V_{DD} = 2.6V V_I = V_{DDO}/GND	—	—	±5	µA
I_{IL}	Input LOW Current(10)	V_{DD} = 2.6V V_I = GND/V_{DDO}	—	—	±5	
V_{IK}	Clamp Diode Voltage	V_{DD} = 2.4V, I_{IN} = -18mA	—	- 0.7	- 1.2	V
V_{IN}	DC Input Voltage		- 0.3		+3.6	V
Single-Ended Inputs(2)						
V_{IH}	DC Input HIGH		1.7		—	V
V_{IL}	DC Input LOW		—		0.7	V
Differential Inputs						
V_{DIF}	DC Differential Voltage(3,9)		0.2		—	V
V_{CM}	DC Common Mode Input Voltage(4,9)		1150	1250	1350	mV
V_{IH}	DC Input HIGH(5,6,9)		V_{REF} + 100		—	mV
V_{IL}	DC Input LOW(5,7,9)		—		V_{REF} - 100	mV
V_{REF}	Single-Ended Reference Voltage(5,9)		—	1250	—	mV
Output Characteristics						
V_{OH}	Output HIGH Voltage	I_{OH} = -12mA	V_{DDO} - 0.4		—	V
		I_{OH} = -100µA	V_{DDO} - 0.1		—	V
V_{OL}	Output LOW Voltage	I_{OL} = 12mA	—		0.4	V
		I_{OL} = 100µA	—		0.1	V

NOTES:

1. See RECOMMENDED OPERATING RANGE table.
2. For 2.5V LVTTL single-ended operation, the RxS pin is tied HIGH and $\overline{A}$/V_{REF} is tied to GND.
3. V_{DIF} specifies the minimum input differential voltage (V_{TR} - V_{CP}) required for switching where V_{TR} is the "true" input level and V_{CP} is the "complement" input level. Differential mode only. The DC differential voltage must be maintained to guarantee retaining the existing HIGH or LOW input. The AC differential voltage must be achieved to guarantee switching to a new state.
4. V_{CM} specifies the maximum allowable range of (V_{TR} + V_{CP}) /2. Differential mode only.
5. For single-ended operation, in differential mode, $\overline{A}$/V_{REF} is tied to the DC voltage V_{REF}.
6. Voltage required to maintain a logic HIGH, single-ended operation in differential mode.
7. Voltage required to maintain a logic LOW, single-ended operation in differential mode.
8. Typical values are at V_{DD} = 2.5V, V_{DDQ} = V_{DD}, +25°C ambient.
9. The reference clock input is capable of HSTL, eHSTL, LVEPECL, 1.8V or 2.5V LVTTL operation independent of the device output. The correct input interface table should be referenced.
10. For differential mode (RxS = LOW), A and $\overline{A}$/V_{REF} must be at the opposite rail.

© 2019 Renesas Electronics Corporation

POWER SUPPLY CHARACTERISTICS FOR 2.5V LVTTL OUTPUTS(1)

Symbol	Parameter	Test Conditions(2)	Typ.	Max	Unit
I_{DDQ}	Quiescent V_{DD} Power Supply Current	V_{DDQ} = Max., Reference Clock = LOW(3) Outputs enabled, All outputs unloaded	20	30	mA
I_{DDQQ}	Quiescent V_{DDQ} Power Supply Current	V_{DDQ} = Max., Reference Clock = LOW(3) Outputs enabled, All outputs unloaded	0.1	0.3	mA
I_{DDD}	Dynamic V_{DD} Power Supply Current per Output	V_{DD} = Max., V_{DDQ} = Max., C_L = 0pF	25	40	µA/MHz
I_{DDDQ}	Dynamic V_{DDQ} Power Supply Current per Output	V_{DD} = Max., V_{DDQ} = Max., C_L = 0pF	40	70	µA/MHz
I_{TOT}	Total Power V_{DD} Supply Current	V_{DDQ} = 2.5V, $F_{REFERENCE\ CLOCK}$ = 100MHz, C_L = 15pF	25	40	mA
		V_{DDQ} = 2.5V, $F_{REFERENCE\ CLOCK}$ = 200MHz, C_L = 15pF	40	70	
I_{TOTQ}	Total Power V_{DDQ} Supply Current	V_{DDQ} = 2.5V, $F_{REFERENCE\ CLOCK}$ = 100MHz, C_L = 15pF	40	80	mA
		V_{DDQ} = 2.5V, $F_{REFERENCE\ CLOCK}$ = 200MHz, C_L = 15pF	100	200	

NOTES:

1. These power consumption characteristics are for all the valid input interfaces and cover the worst case input and output interface combinations.
2. The termination resistors are excluded from these measurements.
3. If the differential input interface is used, the true input is held LOW and the complementary input is held HIGH.

DIFFERENTIAL INPUT AC TEST CONDITIONS FOR 2.5V LVTTL

Symbol	Parameter	Value	Units
V_{DIF}	Input Signal Swing(1)	V_{DD}	V
V_X	Differential Input Signal Crossing Point(2)	$V_{DD}/2$	V
V_{THI}	Input Timing Measurement Reference Level(3)	Crossing Point	V
t_R, t_F	Input Signal Edge Rate(4)	2.5	V/ns

NOTES:

1. A nominal 2.5V peak-to-peak input pulse level is specified to allow consistent, repeatable results in an automatic test equipment (ATE) environment. Compliant devices must meet the V_{DIF} (AC) specification under actual use conditions.
2. A nominal 1.25V crossing point level is specified to allow consistent, repeatable results in an automatic test equipment (ATE) environment. Compliant devices must meet the V_X specification under actual use conditions.
3. In all cases, input waveform timing is marked at the differential cross-point of the input signals.
4. The input signal edge rate of 2.5V/ns or greater is to be maintained in the 20% to 80% range of the input waveform.

SINGLE-ENDED INPUT AC TEST CONDITIONS FOR 2.5V LVTTL

Symbol	Parameter	Value	Units
V_{IH}	Input HIGH Voltage	V_{DD}	V
V_{IL}	Input LOW Voltage	0	V
V_{THI}	Input Timing Measurement Reference Level(1)	$V_{DD}/2$	V
t_R, t_F	Input Signal Edge Rate(2)	2	V/ns

NOTES:

1. A nominal 1.25V timing measurement reference level is specified to allow constant, repeatable results in an automatic test equipment (ATE) environment.
2. The input signal edge rate of 2V/ns or greater is to be maintained in the 10% to 90% range of the input waveform.

© 2019 Renesas Electronics Corporation

DC ELECTRICAL CHARACTERISTICS OVER OPERATING RANGE FOR 1.8V LVTTL(1)

Symbol	Parameter	Test Conditions	Min.	Typ.(8)	Max	Unit
Input Characteristics						
I_{IH}	Input HIGH Current(12)	V_{DD} = 2.6V V_I = V_{DDQ}/GND	—	—	±5	µA
I_{IL}	Input LOW Current(12)	V_{DD} = 2.6V V_I = GND/V_{DDQ}	—	—	±5	
V_{IK}	Clamp Diode Voltage	V_{DD} = 2.4V, I_{IN} = -18mA	—	- 0.7	- 1.2	V
V_{IN}	DC Input Voltage		- 0.3		V_{DDQ} + 0.3	V
Single-Ended Inputs(2)						
V_{IH}	DC Input HIGH		1.073(10)		—	V
V_{IL}	DC Input LOW		—		0.683(11)	V
Differential Inputs						
V_{DIF}	DC Differential Voltage(3,9)		0.2		—	V
V_{CM}	DC Common Mode Input Voltage(4,9)		825	900	975	mV
V_{IH}	DC Input HIGH(5,6,9)		V_{REF} + 100		—	mV
V_{IL}	DC Input LOW(5,7,9)		—		V_{REF} - 100	mV
V_{REF}	Single-Ended Reference Voltage(5,9)		—	900	—	mV
Output Characteristics						
V_{OH}	Output HIGH Voltage	I_{OH} = -6mA	V_{DDQ} - 0.4		—	V
		I_{OH} = -100µA	V_{DDQ} - 0.1		—	V
V_{OL}	Output LOW Voltage	I_{OL} = 6mA	—		0.4	V
		I_{OL} = 100µA	—		0.1	V

NOTES:

1. See RECOMMENDED OPERATING RANGE table.
2. For 1.8V LVTTL single-ended operation, the RxS pin is allowed to float or tied to $V_{DD}/2$ and $\overline{A}/V_{REF}$ is tied to GND.
3. V_{DIF} specifies the minimum input differential voltage (V_{TR} - V_{CP}) required for switching where V_{TR} is the "true" input level and V_{CP} is the "complement" input level. Differential mode only. The DC differential voltage must be maintained to guarantee retaining the existing HIGH or LOW input. The AC differential voltage must be achieved to guarantee switching to a new state.
4. V_{CM} specifies the maximum allowable range of (V_{TR} + V_{CP}) /2. Differential mode only.
5. For single-ended operation in differential mode, $\overline{A}/V_{REF}$ is tied to the DC voltage V_{REF}. The input is guaranteed to toggle within ±200mV of V_{REF} when V_{REF} is constrained within +600mV and V_{DDI}-600mV, where V_{DDI} is the nominal 1.8V power supply of the device driving the A input. To guarantee switching in voltage range specified in the JEDEC 1.8V LVTTL interface specification, V_{REF} must be maintained at 900mV with appropriate tolerances.
6. Voltage required to maintain a logic HIGH, single-ended operation in differential mode.
7. Voltage required to maintain a logic LOW, single-ended operation in differential mode.
8. Typical values are at V_{DD} = 2.5V, V_{DDQ} = 1.8V, +25°C ambient.
9. The reference clock input is capable of HSTL, eHSTL, LVEPECL, 1.8V or 2.5V LVTTL operation independent of the device output. The correct input interface table should be referenced.
10. This value is the worst case minimum V_{IH} over the specification range of the 1.8V power supply. The 1.8V LVTTL specification is V_{IH} = 0.65 • V_{DD} where V_{DD} is 1.8V ± 0.15V. However, the LVTTL translator is supplied by a 2.5V nominal supply on this part. To ensure compliance with the specification, the translator was designed to accept the calculated worst case value (V_{IH} = 0.65 • [1.8 - 0.15V]) rather than reference against a nominal 1.8V supply.
11. This value is the worst case maximum V_{IL} over the specification range of the 1.8V power supply. The 1.8V LVTTL specification is V_{IL} = 0.35 • V_{DD} where V_{DD} is 1.8V ± 0.15V. However, the LVTTL translator is supplied by a 2.5V nominal supply on this part. To ensure compliance with the specification, the translator was designed to accept the calculated worst case value (V_{IL} = 0.35 • [1.8 + 0.15V]) rather than reference against a nominal 1.8V supply.
12. For differential mode (RxS = LOW), A and $\overline{A}/V_{REF}$ must be at the opposite rail.

© 2019 Renesas Electronics Corporation

POWER SUPPLY CHARACTERISTICS FOR 1.8V LVTTL OUTPUTS(1)

Symbol	Parameter	Test Conditions(2)	Typ.	Max	Unit
I_{DDQ}	Quiescent V_{DD} Power Supply Current	V_{DDQ} = Max., Reference Clock = LOW(3) Outputs enabled, All outputs unloaded	20	30	mA
I_{DDQQ}	Quiescent V_{DDQ} Power Supply Current	V_{DDQ} = Max., Reference Clock = LOW(3) Outputs enabled, All outputs unloaded	0.1	0.3	mA
I_{DDD}	Dynamic V_{DD} Power Supply Current per Output	V_{DD} = Max., V_{DDQ} = Max., C_L = 0pF	20	40	µA/MHz
I_{DDDQ}	Dynamic V_{DDQ} Power Supply Current per Output	V_{DD} = Max., V_{DDQ} = Max., C_L = 0pF	55	80	µA/MHz
I_{TOT}	Total Power V_{DD} Supply Current	V_{DDQ} = 1.8V, $F_{REFERENCE\ CLOCK}$ = 100MHz, C_L = 15pF	25	40	mA
		V_{DDQ} = 1.8V, $F_{REFERENCE\ CLOCK}$ = 200MHz, C_L = 15pF	40	60	
I_{TOTQ}	Total Power V_{DDQ} Supply Current	V_{DDQ} = 1.8V, $F_{REFERENCE\ CLOCK}$ = 100MHz, C_L = 15pF	55	110	mA
		V_{DDQ} = 1.8V, $F_{REFERENCE\ CLOCK}$ = 200MHz, C_L = 15pF	130	260	

NOTES:

1. These power consumption characteristics are for all the valid input interfaces and cover the worst case input and output interface combinations.
2. The termination resistors are excluded from these measurements.
3. If the differential input interface is used, the true input is held LOW and the complementary input is held HIGH.

DIFFERENTIAL INPUT AC TEST CONDITIONS FOR 1.8V LVTTL

Symbol	Parameter	Value	Units
V_{DIF}	Input Signal Swing(1)	V_{DDI}	V
V_X	Differential Input Signal Crossing Point(2)	V_{DDI}/2	mV
V_{THI}	Input Timing Measurement Reference Level(3)	Crossing Point	V
t_R, t_F	Input Signal Edge Rate(4)	1.8	V/ns

NOTES:

1. V_{DDI} is the nominal 1.8V supply (1.8V ± 0.15V) of the part or source driving the input. A nominal 1.8V peak-to-peak input pulse level is specified to allow consistent, repeatable results in an automatic test equipment (ATE) environment. Compliant devices must meet the V_{DIF} (AC) specification under actual use conditions.
2. A nominal 900mV crossing point level is specified to allow consistent, repeatable results in an automatic test equipment (ATE) environment. Compliant devices must meet the V_X specification under actual use conditions.
3. In all cases, input waveform timing is marked at the differential cross-point of the input signals.
4. The input signal edge rate of 1.8V/ns or greater is to be maintained in the 20% to 80% range of the input waveform.

SINGLE-ENDED INPUT AC TEST CONDITIONS FOR 1.8V LVTTL

Symbol	Parameter	Value	Units
V_{IH}	Input HIGH Voltage(1)	V_{DDI}	V
V_{IL}	Input LOW Voltage	0	V
V_{THI}	Input Timing Measurement Reference Level(2)	V_{DDI}/2	mV
t_R, t_F	Input Signal Edge Rate(3)	2	V/ns

NOTES:

1. V_{DDI} is the nominal 1.8V supply (1.8V ± 0.15V) of the part or source driving the input.
2. A nominal 900mV timing measurement reference level is specified to allow constant, repeatable results in an automatic test equipment (ATE) environment.
3. The input signal edge rate of 2V/ns or greater is to be maintained in the 10% to 90% range of the input waveform.

© 2019 Renesas Electronics Corporation

AC ELECTRICAL CHARACTERISTICS OVER OPERATING RANGE(7)

Symbol	Parameter		Min.	Typ.	Max	Unit
Skew Parameters						
$t_{SK(O)}$	Same Device Output Pin-to-Pin Skew(1)	Single-Ended and Differential Modes	—	—	125	ps
		Single-Ended in Differential Mode (DSE)	—	125	—	
$t_{SK(P)}$(2)	Pulse Skew(3)	Single-Ended and Differential Modes	—	—	300	ps
		Single-Ended in Differential Mode (DSE)	—	300	—	
$t_{SK(P)}$(4)	Pulse Skew(3)	Single-Ended and Differential Modes	—	—	350	ps
		Single-Ended in Differential Mode (DSE)	—	350	—	
d_T(5)	Duty Cycle		40	—	60	%
$t_{SK(PP)}$	Part-to-Part Skew(6)	Single-Ended and Differential Modes	—	—	300	ps
		Single-Ended in Differential Mode (DSE)	—	300	—	
Propagation Delay						
t_{PLH} t_{PHL}	Propagation Delay A to Qn		—	—	2.5	ns
t_R	Output Rise Time (20% to 80%)	2.5V / 1.8V LVTTL Outputs	350	—	1050	ps
		HSTL / eHSTL Outputs	350	—	1350	
t_F	Output Fall Time (20% to 80%)	2.5V / 1.8V LVTTL Outputs	350	—	1050	ps
		HSTL / eHSTL Outputs	350	—	1350	
f_O	Frequency Range (HSTL/eHSTL outputs)		—	—	250	MHz
	Frequency Range (2.5V/1.8V LVTTL outputs)		—	—	200	
Output Gate Enable/Disable Delay						
t_{PGE}	Output Gate Enable to Qn		—	—	3.5	ns
t_{PGD}	Output Gate Enable to Qn Driven to GL Designated Level		—	—	3	ns

NOTES:

1. Skew measured between all outputs under identical input and output interfaces, transitions, and load conditions on any one device.
2. For 1.8V LVTTL and eHSTL outputs only.
3. Skew measured is difference between propagation times t_{PLH} and t_{PHL} of any output under identical input and output interfaces, transitions, and load conditions on any one device.
4. For 2.5V LVTTL outputs only.
5. For HSTL outputs only.
6. Skew measured is the magnitude of the difference in propagation times between any outputs of two devices, given identical transitions and load conditions at identical V_{DD}/V_{DDQ} levels and temperature.
7. Guaranteed by design.

© 2019 Renesas Electronics Corporation

AC DIFFERENTIAL INPUT SPECIFICATIONS(1)


Symbol	Parameter	Min.	Typ.	Max	Unit
t_W	Reference Clock Pulse Width HIGH or LOW (HSTL/eHSTL outputs)(2)	1.73	—	—	ns
	Reference Clock Pulse Width HIGH or LOW (2.5V / 1.8V LVTTL outputs)(2)	2.17	—	—	
HSTL/eHSTL/1.8V LVTTL/2.5V LVTTL					
V_{DIF}	AC Differential Voltage(3)	400	—	—	mV
V_{IH}	AC Input HIGH(4,5)	Vx + 200	—	—	mV
V_{IL}	AC Input LOW(4,6)	—	—	Vx - 200	mV
LVEPECL					
V_{DIF}	AC Differential Voltage(3)	400	—	—	mV
V_{IH}	AC Input HIGH(4)	1275	—	—	mV
V_{IL}	AC Input LOW(4)	—	—	875	mV

NOTES:

1. For differential input mode, RxS is tied to GND.
2. Both differential input signals should not be driven to the same level simultaneously. The input will not change state until the inputs have crossed and the voltage range defined by V_{DIF} has been met or exceeded.
3. Differential mode only. V_{DIF} specifies the minimum input voltage (V_{TR} - V_{CP}) required for switching where V_{TR} is the "true" input level and V_{CP} is the "complement" input level. The AC differential voltage must be achieved to guarantee switching to a new state.
4. For single-ended operation, $\overline{A}/V_{REF}$ is tied to DC voltage (V_{REF}). Refer to each input interface's DC specification for the correct V_{REF} range.
5. Voltage required to switch to a logic HIGH, single-ended operation only.
6. Voltage required to switch to a logic LOW, single-ended operation only.

© 2019 Renesas Electronics Corporation

AC TIMING WAVEFORMS




Propagation and Skew Waveforms

NOTES:

1. t_{PHL} and t_{PLH} signals are measured from the input passing through V_{THI} or input pair crossing to Qn passing through V_{THO}.
2. Pulse Skew is calculated using the following expression:

   $$t_{SK(P)} = | t_{PHL} - t_{PLH} |$$

   where t_{PHL} and t_{PLH} are measured on the controlled edges of any one output from rising and falling edges of a single pulse. Please note that the t_{PHL} and t_{PLH} shown are not valid measurements for this calculation because they are not taken from the same pulse.




Gate Disable/Enable Showing Runt Pulse Generation

NOTE:

As shown, it is possible to generate runt pulses on gate disable and enable of the outputs. It is the user's responsibility to time their $\overline{Gx}$ signals to avoid this problem.

© 2019 Renesas Electronics Corporation

TEST CIRCUITS AND CONDITIONS



Test Circuit for Differential Input(1)


DIFFERENTIAL INPUT TEST CONDITIONS

Symbol	V_{DD} = 2.5V ± 0.1V	Unit
R1	100	Ω
R2	100	Ω
V_{DDI}	V_{CM}*2	V
V_{THI}	HSTL: Crossing of A and $\overline{A}$ eHSTL: Crossing of A and $\overline{A}$ LVEPECL: Crossing of A and $\overline{A}$ 1.8V LVTTL: V_{DDI}/2 2.5V LVTTL: V_{DD}/2	V

NOTE:

1. This input configuration is used for all input interfaces. For single-ended testing, the V_{IN} input is tied to GND. For testing single-ended in differential input mode, the V_{IN} is left floating.

© 2019 Renesas Electronics Corporation




Test Circuit for SDR Outputs

SDR OUTPUT TEST CONDITIONS

Symbol	V_{DD} = 2.5V ± 0.1V V_{DDQ} = Interface Specified	Unit
C_L	15	pF
R1	100	Ω
R2	100	Ω
V_{THO}	V_{DDQ} / 2	V

© 2019 Renesas Electronics Corporation

ORDERING INFORMATION



© 2019 Renesas Electronics Corporation

REVISION HISTORY

Rev	Table	Page	Discription of Change	Date
A		1	NRND - Not Recommended for New Designs	5/20/13
A		17	Ordering Information - Removed PA leaded device. Updated data sheet format.	4/14/15
A		1	Product discontinuation notice - last time buy expires September 7, 2016. PDN# N-16-02	

© 2019 Renesas Electronics Corporation

IMPORTANT NOTICE AND DISCLAIMER

RENESAS ELECTRONICS CORPORATION AND ITS SUBSIDIARIES (“RENESAS”) PROVIDES TECHNICAL SPECIFICATIONS AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES “AS IS” AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING, WITHOUT LIMITATION, ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for developers skilled in the art designing with Renesas products. You are solely responsible for (1) selecting the appropriate products for your application, (2) designing, validating, and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. Renesas grants you permission to use these resources only for development of an application that uses Renesas products. Other reproduction or use of these resources is strictly prohibited. No license is granted to any other Renesas intellectual property or to any third party intellectual property. Renesas disclaims responsibility for, and you will fully indemnify Renesas and its representatives against, any claims, damages, costs, losses, or liabilities arising out of your use of these resources. Renesas' products are provided only subject to Renesas' Terms and Conditions of Sale or other applicable terms agreed to in writing. No use of any Renesas resources expands or otherwise alters any applicable warranties or warranty disclaimers for these products.

(Rev.1.0 Mar 2020)

Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu,
Koto-ku, Tokyo 135-0061, Japan
www.renesas.com

Contact Information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit:
www.renesas.com/contact/

Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

© 2020 Renesas Electronics Corporation. All rights reserved.