

18X18W RGBWA UV 6in1

LED Wall Wash Light

USER MANUAL



Please read over this manual before operation the light

1. The Introduction of LED display panel:



- A. Menu
- B. UP
- C. Down
- D. Enter

A B C D

Press **A** button, there will be eight different effects.

The first two letters stands for functions (refer to Diagram II)

The last two letters stands for DMX address, or speed,.

You can modify it with **B** or **C** button. And press **D** button for confirmation.

2. Function of LED Display Window (press button **D** to confirm all the function)

No	Display	Function
1	A001	10 channel , with B. C button to change the code(001-512)
2	D001	6 channel , with B. C button to change the code(001-512)
3	CC00	Jump(01-99), with B. C button to change the speed
4	CP00	Fade(01-99), with B. C button to change the speed

5	DE00	pulse(01-99), with B. C button to change the speed
6	BEB1	Sound change
7	R220	Red color, with B. C button to change the color(0-255)
8	G220	Green color, with B. C button to change the color(0-255)
9	B220	Blue color, with B. C button to change the color(0-255)
10	W220	White color, with B. C button to change the color(0-255)
11	Y220	Amber color, with B. C button to change the color(0-255)
12	P220	Purple color, with B. C button to change the color(0-255)

3. DMX Channel DMX512 10CH

Channel	Function	Explanation
CH1	Dimmer	linear 0%-100% dimmer, from dark to bright
CH2	Strobe	Strobe from slow to fast
CH3	Control Mode selection	0-50: DMX control 51-100: jump running; 101--150: fade running; 151--200: pulse running; 201--255: sound active;
CH4	Control Mode Speed	From slow to fast
CH5	R Dimmer	linear 0%-100% dimmer, from dark to bright
CH6	G Dimmer	linear 0%-100% dimmer, from dark to bright

CH7	B Dimmer	linear 0%-100% dimmer, from dark to bright
CH8	W Dimmer	linear 0%-100% dimmer, from dark to bright
CH9	Y Dimmer	linear 0%-100% dimmer, from dark to bright
CH10	P Dimmer	linear 0%-100% dimmer, from dark to bright

4.DMX512 6CH

Channel	Function	Explanation
CH1	R Dimmer	linear 0%-100% dimmer, from dark to bright
CH2	G Dimmer	linear 0%-100% dimmer, from dark to bright
CH3	B Dimmer	linear 0%-100% dimmer, from dark to bright
CH4	W Dimmer	linear 0%-100% dimmer, from dark to bright
CH5	Y Dimmer	linear 0%-100% dimmer, from dark to bright
CH6	P Dimmer	linear 0%-100% dimmer, from dark to bright

4. Feature

Easy to operate, humanization design, no flicker while dimmer; Stable quality.