

User's Manual



**18pcs 18W RGBWA UV 6in1
LED Par Light**

1. PACKAGE CONTENTS

1× waterproof 18pcs 18w rgbwa uv 6in1 LED par light

1×AC power cable

1×Signal cable

1×User's manual

2. MENU DISPLAY

Item	Display	Value	Remark
1	A001	A001-255	DMX512 Address, 10 channels
2	D001	D001-255	DMX512 Address, 6 channels
3	CC00	001-99	Color jumping mode
4	CP99	001-99	Color gradient mode
5	dE99	001-99	Color pulse variable mode
6	SOUd	001-99	Sound control model
7	R255	001-255	Red Dimmer
8	G255	001-255	Green Dimmer
9	B255	001-255	Blue Dimmer
10	W255	001-255	White Dimmer
11	Y255	001-255	Amber Dimmer
12	P255	001-255	Purple Dimmer

3. Technical Parameter

Input voltage: AC100-240V

Power consumption: max 150w

LEDs: 18pcs 18w RGBWA UV 6-in-1 LEDs

Flicker free

Lifespan:50,000 hours

Control mode: Stand alone/Master/Slaver/Auto/DMX512

DMX channels: 6CH,10CH

Color effect: R.G.B.W.A.UV mixing

Function effect: dimmer/strobe/eotic/gradual change

putter adaptive cushioning technology

Beam angle: 25°/40° optional

Cooling mode: Natural

convection: Built-in dual temperature control function

Protecting rate: IP20

4. DMX512 Channels

10 Channels

Channel	Function	Value	Remark
1	Master Dimmer	001-255	From dark to bright
2	Strobe	001-255	From slow to fast
3	Function	0-50	DMX control mode
		51-100	Color jumping mode
		100-150	Color gradient mode
		151-200	Color pulse variable mode
		201-255	Sound control model
4	Program Speed	001-255	From slow to fast
5	Red Dimmer	001-255	From dark to bright
6	Green Dimmer	001-255	From dark to bright
7	Blue Dimmer	001-255	From dark to bright
8	White Dimmer	001-255	From dark to bright
9	Amber Dimmer	001-255	From dark to bright
10	Purple Dimmer	001-255	From dark to bright

6 Channels

Channel	Function	Value	Remark
1	Red Dimmer	001-255	From dark to bright
2	Green Dimmer	001-255	From dark to bright
3	Blue Dimmer	001-255	From dark to bright
4	White Dimmer	001-255	From dark to bright
5	Amber Dimmer	001-255	From dark to bright
6	Purple Dimmer	001-255	From dark to bright