

User's Manual



18pcs 10W RGBW 4in1 LED Flat Par Light

1. PACKAGE CONTENTS

1×18pcs 10W RGBW 4in1 LED Flat Par Light

1×Signal Cable

1×User's Manual

2. CONTROLS



MENU: press the MENU button to cycle through the function in the menu system. If editing a value, pressing the MENU button will cancel any changes made and will cycle to the next function in the list.

UP: Press the UP button to decrease the displayed value.

DOWN: Press the DOWN button to increase the displayed value

ENTER: Press the ENTER button to save the displayed value.

UP: Press the UP button to decrease the displayed value.

DOWN: Press the DOWN button to increase the displayed value



Black board

3. MENU FUNCTION

Item	Function	Description
1	A001	A001-512
2	D001	D001-512
3	R255	R001-255
4	G255	G001-255
5	B255	B001-255
6	W255	W001-255
7	F000	F000-255
8	DE15	DE00-15
9	CC15	00-15
10	CP15	CP00-15
11	SOUD	

4. DMX512 MODE

4 Channels

CH	Function	Value
1	Red	001-255
2	Green	001-255
3	Blue	001-255
4	White	001-255

8 Channels

CH	Function	Value
1	Master Dimmer	001-255
2	Red	001-255
3	Green	001-255
4	Blue	001-255
5	White	001-255
6	Strobe	001-255
7	Macro	001-255
8	Macro speed	001-255

5. TECHNICAL PARAMETER

Power supply: AC100V-240V

Frequency: 50/60Hz

Power consumption: 130W

Light source: 18pcs 10W RGBW 4in1 leds

Beam Angle: 40°

Lamp life: 50,000 hrs

Control channels: 4CH/8CH

Control mode: DMX512, master-slave, auto, sound

Operation menu: 4 digit digital LED display

Body: 24*22*24cm

Carton size: 25*25*36cm

N.W: 2.5kg

G.W: 3.5kg